



THE TELOS ALLIANCE®

Create. Communicate. Connect.

iProFiler Server v2.5.25 Installation Instructions

With iProFiler Client v2.5.9, and Version Notes

November 13, 2015

This document details the installation of the newest version of iProFiler Server, v2.5.25, which is compatible with the latest Windows OS releases, through Windows 10.

The distribution ZIP file **iProFiler2.5.25complete.zip** includes the following files:

- **iProFiler2.5.25-install.pdf** (this file)
- **iProFilerServer2.5.25.msi** (Server installation executable)
- **iProFilerClient259.msi** (Client installation executable)

You should unzip the contents of the ZIP file to an easily-found folder on the PC from which you plan to install the software.

Before Upgrading From Earlier Versions

To upgrade, you must stop iProFiler Server and iProFiler Client (if running) and any connected iProFiler Client applications.

Server installation

Before beginning installation, please locate the key codes that were supplied with your original iProFiler packaging. You will need them to complete the upgrade.

1. Open your Windows Control Panel (Start → Control Panel) and choose “Add or Remove Programs”.
2. Select iProFiler Server and click “Remove”. Choose “Yes” when asked to confirm.
3. When the uninstall process is finished, navigate to the folder into which the installer files were extracted. Double-click on the **iProFilerServer2.5.25.msi** file and follow the installation instructions on-screen.
4. When asked for a key code, enter the codes supplied with your original iProFiler package, or supplied by Telos when your software was purchased.
5. The installation procedure will complete. If you have previously activated your iProFiler package, you will not be prompted to activate it again.



Client installation

1. Open your Windows Control Panel (Start → Control Panel) and choose “Add or Remove Programs”.
2. Select iProFiler Client and click “Remove”. Choose “Yes” when asked to confirm.
3. When the uninstall process is finished, navigate to the folder into which the installer files were extracted. Double-click on the **iProFilerClient259f.msi** file and follow the installation instructions on-screen.

Version Notes

iProFiler v2.5.25 includes the following updates from v2.5.9f:

- iProFiler Server has been modified with compatibility for the most recent MS Windows operating systems.

iProFiler v2.5.9f includes the following updates from v2.5.9:

- The bundled version of the Axia IP-Audio Driver for Windows has been updated to v2.5.2.3. This increases the maximum number of stereo Livewire channels supported to 24.

iProFiler v2.5.9 includes the following fixes and updates from v2.5.6:

- The Open Archive dialog allows the user to specify the date range to view upon connect. In previous versions, the dialog was improperly initialized. The fix changes the way the date is saved to the registry to avoid date format dependencies.
- Audio sources are now labeled as “L & R” instead of “L + R” for clarity.
- iProFiler Server now allows users to select the size of the recorded audio segments. While this is useful for special applications, the default size of 15 minutes will work best when accessing the archive via Archive Player.
- Fixed a bug where the bit rate reset to zero when switching between “Skim” and “Continuous” recording modes.
- Fixed a bug where the Archive Player would not select the proper hours when the time filter was being applied.





THE TELOS ALLIANCE®

Create. Communicate. Connect.

- In previous versions, when the iProFiler Server was unable to erase a segment, it would stop erasing further segments. Now, it will repeat the unsuccessful erase attempt for a short time, then skip the unerasable segment and continue to erase other segments to keep disk usage limits within user specified ranges.
- Fixed a bug where the Axia GPIO plug-in did not initialize properly.
- Users can now select both IN and OUT GPIO signals.
- Player now properly plays 8kbps audio streams.
- Fixed a bug that caused the Scheduler to continue recording past the end time if the end time was set to 11:59:59.
- Auto startup of archives now works correctly.

Contact us

If you have questions or need further assistance with this installation, please contact Telos Alliance Support at support@TelosAlliance.com.



1241 Superior Avenue Cleveland, OH 44114 USA | +1.216.241.7225 | TelosAlliance.com